

## BOŞLUKSUZ SERVO KAPLINLER



PARÇA NO	İç Çap		Dış Çap	Boy	Max.Tork (Nm)	Max.Hız (rpm)
	Min	Max				
SJC14C-RD <b>GS 07</b>	3	5	14	22	4	22000
SJC20C-RD <b>GS 09</b>	4	8	20	30	10	11000
SJC25C-RD <b>GS 12</b>	5	10	25	32,5	20	10000
SJCB30C-RD <b>GS 14</b>	6	14	30	44	28	10000
SJCB40C-RD <b>GS 19</b>	8	18	40	66	36	8500
SJC55C-RD <b>GS 24</b>	12	28	55	78	120	6500
SJC65C-RD <b>GS 28</b>	15	35	65	90	360	5500
SJC80C-RD <b>GS 38</b>	15	45	80	114	640	4500
PARÇA NO	İç Çap		Dış Çap	Boy	Max.Tork (Nm)	Max.Hız (rpm)
	Min	Max				
SDWB-22 C	3	8	22,2	27	2,2	10000
SDWB-31 C	5	14	31,8	38,5	6	8500
SDWB-42 C	6	17	42,5	44,2	12	8000
SDWB-47 C	8	20	47,0	51,3	20	7500
SDWB-54 C	10	25	54,0	52	44	7000
SDW-90 C	20	45	94,5	98	300	6000
PARÇA NO	İç Çap		Dış Çap	Boy	Max.Tork (Nm)	Max.Hız (rpm)
	Min	Max				
SHDS-56C	10	25	56	44,2	60	7700
SHDS-66C	15	32	66	56,5	120	7000
SHDS-88C	20	45	88	69,5	200	6000
SHDW-56C	10	25	56	60,5	60	7700
SHDW-66C	15	32	66	80	120	7000
SHDW-88C	20	45	88	99,2	200	6000
PARÇA NO	İç Çap		Dış Çap	Boy	Max.Tork (Nm)	Max.Hız (rpm)
	Min	Max				
SOH-16C	3	6	16	21	2	8000
SOH-20C	4	8	20	22,5	3	7000
SOH-25C	5	10	25,5	32	5	6000
SOH-32C	6	15	32	45	14	4800
SOH-43C	8	19	43	52	30	4000
SOH-53C	10	25	53	58	50	3400
SOHM-70C	18	35	73	77	130	3000
PARÇA NO	İç Çap		Dış Çap	Boy	Max.Tork (Nm)	Max.Hız (rpm)
	Min	Max				
SRBM-12 C	3	5	12,7	14	0,4	20000
SRBM-16 C	3	6	16,0	16	0,8	20000
SRBM-19 C	4	8	19,1	17	1,2	19000
SRBM-22 C	5	10	22,2	20	2	17000
SRBM-26 C	5	12	26,2	23	3	15000
SRBM-32 C	6	15	31,8	30	5,2	10000